


Instruction

The DNAKE S213M enables you to make the video call with villa entrance door, and open the door remotely from indoor monitor or mobile APP. It also makes an easy integration with SIP devices.

DNAKE S213M (Surface Mounting)



Key Features

- Powered by PoE or power adapter (DC12V/2A)
- Support IC (13.56MHz) & ID (125kHz) card, NFC
- 3 Indicator Lights
- 2 relays supported
- Tamper alarm
- Multi-button supported (2 or 5 buttons optional)

Physical

- System: Linux
- RAM: 64 MB
- ROM: 128 MB
- Front Panel: Aluminum
- Power Supply: PoE (802.3af) or DC 12V/2A
- Standby Power: 1.5 W
- Rated Power: 3.5 W
- Camera: 2MP, CMOS
- Indicator Light: 3
- Wiegand Port: Support
- Ethernet Port: 1 x RJ45, 10/100 Mbps adaptive
- Door Entry: IC (13.56MHz) & ID (125kHz) card, NFC
- Reset Button: 1
- RS485 Port: 1
- Relay Out: 2
- Input: 2
- IP / IK Rating: IP65 / IK08
- Installation: Surface Mounting
- Surface Mounting DIM: 188 x 88 x 34 mm
- Working Temperature: -40°C to +55°C
- Storage Temperature: -40°C to +70°C
- Working Humidity: 10% to 90% (non-condensing)



Datasheet

Audio

- Audio Codec: G.711
- Echo Cancellation
- DTMF: RFC2833
- Microphone: Built-in microphone
- Speaker: Built-in speaker

Video

- Video Codec: H.264
- Video Resolution: 1280 x 720
- Viewing Angle: 110° (H) / 60° (V) / 125° (D)
- Max. Image Transfer Rate: 720p – 30fps
- Light Compensation: LED white light

Networking

- Protocol: ONVIF, SIP, UDP, TCP, RTP, RTSP, NTP, DNS, HTTP, DHCP, IPV4, ARP, ICMP

Package Features


- Package Content:
 - DNAKE S213M
(Power adapter not included)
 - Bracket
 - Screwing Kit
 - Quick Start Guide



Instruction

The DNAKE S213M enables you to make the video call with villa entrance door, and open the door remotely from indoor monitor or mobile APP. It also makes an easy integration with SIP devices.

DNAKE S213M (Flush Mounting)



Key Features

- Powered by PoE or power adapter (DC12V/2A)
- Support IC (13.56MHz) & ID (125kHz) card, NFC
- 3 Indicator Lights
- 2 relays supported
- Tamper alarm
- Multi-button supported (2 or 5 buttons optional)

Physical

- System: Linux
- RAM: 64 MB
- ROM: 128 MB
- Front Panel: Aluminum
- Power Supply: PoE (802.3af) or DC 12V/2A
- Standby Power: 1.5 W
- Rated Power: 3.5 W
- Camera: 2MP, CMOS
- Indicator Light: 3
- Wiegand Port: Support
- Ethernet Port: 1 x RJ45, 10/100 Mbps adaptive
- Door Entry: IC (13.56MHz) & ID (125kHz) card, NFC
- Reset Button: 1
- RS485 Port: 1
- Relay Out: 2
- Input: 2
- IP / IK Rating: IP65 / IK08
- Installation: Flush Mounting
- Flush Mounting DIM: 230 x 120 x 48 mm
- Working Temperature: -40°C to +55°C
- Storage Temperature: -40°C to +70°C
- Working Humidity: 10% to 90% (non-condensing)



Datasheet

Audio

- Audio Codec: G.711
- Echo Cancellation
- DTMF: RFC2833
- Microphone: Built-in microphone
- Speaker: Built-in speaker

Video

- Video Codec: H.264
- Video Resolution: 1280 x 720
- Viewing Angle: 110° (H) / 60° (V) / 125° (D)
- Max. Image Transfer Rate: 720p – 30fps
- Light Compensation: LED white light

Networking

- Protocol: ONVIF, SIP, UDP, TCP, RTP, RTSP, NTP, DNS, HTTP, DHCP, IPV4, ARP, ICMP

Package Features

- Package Content:
 - DNAKE S213M
(Power adapter not included)
 - Flush Mounting Box
 - Front Aluminum Panel
 - Screwing Kit
 - Quick Start Guide

