


## Instruction

8 Relays & Input Module is an economical automation control module. It is paired with Indoor Monitor and Smart Pro App to realize a small entry-level home control solution.

## RIM08



## Key Features

- Control different devices, such as lights, heating, natural gas, curtains, water valves, etc.
- Support different control entrances including relay module, indoor monitor, and APP
- Powered by PoE or power adapter (DC12V/2A)
- Support remote control of device
- Rail mounting

## Physical

- Material: Plastic
- RAM: 64 MB
- ROM: 128 MB
- Power Supply: PoE (802.3af) or DC 12V/1A
- Rated Power: 5 W
- Ethernet Port: 1 x RJ45, 10/100 Mbps adaptive
- Reset Button: 1
- RS485 Port: 1
- Relay Output: 8
- Alarm Input: 8
- Dimension: 91 x 145 x 61 mm
- Working Temperature: -10°C to +55°C
- Storage Temperature: -40°C to +70°C
- Working Humidity: 10% to 90% (non-condensing)
- Installation: Rail mounting

